



- using UHF wireless microphone special frequency, without interference from other industrial frequency.
- PLL digital frequency synthesis technology, provides up to 200 selected working channel, realize the simultaneous use of multiple machines.
- use infrared frequency synchronization technology, the transmitter operation is simple and convenient.
- In the transmitter power adjustable. When outdoor use, the choice of high power, the use of distance far, in the classroom or KTV occasions when using low power, can reduce the interference, save battery.
- In the pilot data control technology, effectively prevent the impact of radio frequency interference and other acoustic transmitter switch machine.
- In the transmitter uses 2 1.5V/AA batteries power supply, battery used for a long time, more convenient maintenance.
- with balanced and unbalanced audio output, convenient connection and various audio equipment.
- In the receiver can display parameters of the transmitter, which is convenient for monitoring.
- In the transmitter is made of high strength alloy materials, durable.

Wireless Receiver

GR-5600

- In the frequency range: Channel: A/B: 694~703 MHz
Channel: C/D: 748~758 MHz
- Number of channels: Four channel
- maximum deviation: + 15KHz
- In the letter: exercise than >100dB
- comprehensive distortion: less than 0.02%
- frequency stability: + 0.03%
- audio response: + 40 Hz-16 KHz
- dynamic range: >100dB
- rated working current: 480 Ma
- working temperature: -20 to +50 DEG C
- rated working current: 150 mA
- Power supply: AC 220V/50Hz

Handheld transmitter

GR-5600A / GR-5600B / GR-5600C /GR-5600D

- Carrier frequency: Channel: A/B: 694~703 MHz
Channel: C/D: 748~758 MHz
- maximum deviation: + 15KHz
- In the letter: exercise than >100dB
- comprehensive distortion: less than 0.02%
- frequency stability: + 0.03%
- audio response: + 40 Hz-16 KHz
- dynamic range: >100dB
- Power: 8.5mW
- battery time: >8 hours
- Battery: AA x 2

[E₃][®]
TR-820

UHF PROFESSIONAL WIRELESS MICROPHONE



- EIA international standard 1U metal chassis with a new design, True Diversity Dual channel receiver assembly.
- panel the color active luminous LCD display screen glance display of the.
- functions and data, and is easy to operate Jog Dial to replace the traditional complex key operation.
- Fast and accurate digital diversity receiver, to eliminate interruption, longer receive distance and enhance the stability of the receiver.
- the sound quality is a pure digital processing manner, so that the wireless transmission quality of the microphone almost reached the level of the wired transmission.
- the original pure digital high-fidelity audio processing technology, the complete elimination of analog compression noise regeneration waveform almost the same as the original waveform to ensure Sounds perfect reproduction.
- full-range sound quality of the of purely digital wireless transmission, not with the received signal strength or use distance change Electronic volume.
- output control, clear and intuitive operation.

Wireless Receiver

TR-820

- In the frequency range: Channel A : 694-703 MHz
Channel B : 748-758 MHz
- Number of channels: Dual channel
- Modulation Mode: FM
- Oscillation mode: PLL phase-locked frequency synthesizer
- Band width: 30MHz
- Sensitivity: The degree of offset is equal to 25KHz, Input 6dBv, S/N >60dB
- Maximum deviation: ±45KHz
- Comprehensive S/N ratio: >105dB
- Comprehensive T.H.D: <0.7% @ 1KHz
- Frequency response: 45Hz ~ 18KHz ±3dB
- Output connector: XLR parallel and 6.3 parallel socket
- Power supply: AC 220V/50Hz

Handheld transmitter

TR-820A / TR-820B

- In the frequency range: Channel A : 694-703 MHz
Channel B : 748-758 MHz
- Oscillation mode: PLL phase-locked frequency synthesizer
- Harmonic radiation: <-65dBm
- Maximum deviation: ±45KHz
- Frequency response: 45Hz ~ 18KHz±3dB
- Capsule: Dynamic
- RF power output: 10MW
- Battery: AA x 2
- Current consumption: <100mA
- Continuous working time: <10 hours



TR-880

Multifunctional wireless microphone



Wireless Receiver TR-880

- Carrier frequency: Channel A: UHF 694~703 MHz
Channel B: UHF 748~ 758MHz
- Number of channels: Dual channel
- Modulation Mode: FM
- Oscillation mode: PLL phase-locked frequency synthesizer
- Band width: 30MHz
- Sensitivity: The degree of offset is equal to 25KHz, Input 6dBv, S/N >60dB
- Maximum deviation: ± 45 KHz
- Comprehensive S/N ratio: >105dB
- Comprehensive T.H.D: <0.7% @ 1KHz
- Frequency response: 45Hz ~ 18KHz ± 3 dB
- Output connector: XLR parallel and 6.3 parallel socket
- Power supply: DC 12V/ 600mA

Handheld transmitter TR-880A / TR-880B

- Carrier frequency: Channel A: UHF 694~703 MHz
Channel B: UHF 748~ 758MHz
- Oscillation mode: PLL phase-locked frequency synthesizer
- Harmonic radiation: <-65dBm
- Maximum deviation: ± 45 KHz
- Frequency response: 45Hz ~ 18KHz ± 3 dB
- Capsule: Dynamic
- RF power output: 10mW
- Battery: AA x 2
- Current consumption: <100mA
- Continuous working time: <10 hours



มอก. 62368
เล่ม 1-2563

บริษัท โปรยโร เทค จำกัด





ER-3000

Professional performance



Wireless Receiver ER-3000

- Carrier frequency: Channel A: UHF 694~703 MHz
Channel B: UHF 748~ 758MHz
- Number of channels: Dual channel
- Modulation Mode: FM
- Oscillation mode: PLL phase-locked frequency synthesizer
- Band width: 30MHz
- Sensitivity: The degree of offset is equal to 25KHz, Input 6dBv, S/N >60dB
- Maximum deviation: ± 45 KHz
- Comprehensive S/N ratio: >105dB
- Comprehensive T.H.D: <0.7% @ 1KHz
- Frequency response: 45Hz ~ 18KHz ± 3 dB
- Output connector: XLR parallel and 6.3 parallel socket
- Power supply: DC 12V/1.25A

Handheld transmitter ER-3000A / ER-3000B

- Carrier frequency: Channel A: UHF 694~703 MHz
Channel B: UHF 748~ 758MHz
- Oscillation mode: PLL phase-locked frequency synthesizer
- Harmonic radiation: <-65dBm
- Maximum deviation: ± 45 KHz
- Frequency response: 45Hz ~ 18KHz ± 3 dB
- Capsule: Dynamic
- RF power output: 10mW
- Battery: AA x 2
- Current consumption: <100mA
- Continuous working time: <10 hours



มอก. 62368
เล่ม 1-2563

บริษัท โปรยโร เทคโนโลยี จำกัด





ER-3200

Professional performance



Wireless Receiver ER-3200

- Carrier frequency: Channel A: UHF 694~703 MHz
Channel B: UHF 748~ 758MHz
- Number of channels: Dual channel
- Modulation Mode: FM
- Oscillation mode: PLL phase-locked frequency synthesizer
- Band width: 30MHz
- Sensitivity: The degree of offset is equal to 25KHz, Input 6dBv, S/N >60dB
- Maximum deviation: ± 45 KHz
- Comprehensive S/N ratio: >105dB
- Comprehensive T.H.D: <0.7% @ 1KHz
- Frequency response: 45Hz ~ 18KHz ± 3 dB
- Output connector: XLR parallel and 6.3 parallel socket
- Power supply: DC 12V/1.25A

Handheld transmitter ER-3200A / ER-3200B

- Carrier frequency: Channel A: UHF 694~703 MHz
Channel B: UHF 748~ 758MHz
- Oscillation mode: PLL phase-locked frequency synthesizer
- Harmonic radiation: <-65dBm
- Maximum deviation: ± 45 KHz
- Frequency response: 45Hz ~ 18KHz ± 3 dB
- Capsule: Dynamic
- RF power output: 10mW
- Battery: AA x 2
- Current consumption: <100mA
- Continuous working time: <10 hours



มอก. 62368
เล่ม 1-2563

บริษัท โปรยโร เทค จำกัด

