

[E₃][®]

TR-880

Multifunctional wireless microphone

new

new

new



Wireless Receiver

TR-880

- Carrier frequency: Channel A: UHF 694~703 MHz
Channel B: UHF 748~ 758MHz
- Number of channels: Dual channel
- Modulation Mode: FM
- Oscillation mode: PLL phase-locked frequency synthesizer
- Band width: 30MHz
- Sensitivity: The degree of offset is equal to 25KHz, Input 6dBv, S/N >60dB
- Maximum deviation: ±45KHz
- Comprehensive S/N ratio: >105dB
- Comprehensive T.H.D: <0.7% @ 1KHz
- Frequency response: 45Hz ~ 18KHz ±3dB
- Output connector: XLR parallel and 6.3 parallel socket
- Power supply: DC 12V/ 600mA

Handheld transmitter

TR-880A / TR-880B

- Carrier frequency: Channel A: UHF 694~703 MHz
Channel B: UHF 748~ 758MHz
- Oscillation mode: PLL phase-locked frequency synthesizer
- Harmonic radiation: <-65dBm
- Maximum deviation: ±45KHz
- Frequency response: 45Hz ~ 18KHz±3dB
- Capsule: Dynamic
- RF power output: 10mW
- Battery: AA x 2
- Current consumption: <100mA
- Continuous working time: <10 hours



શ્રાવણ ૬૩૧૦૮

તા. ૧-૨૬૦૩

શ્રીમદ્ ભાઈજીભાઈ શાહ

